



Data Specs

25W 5V~5A AC-DC Power Adapter

General purpose 25W AC-DC external desktop power supplies with low profile insulated enclosure. Wide AC input range with high average efficiency of 87% and a low offload power consumption of <0.5W. Typical applications for these AC-DC external desktop power supplies include portable equipment, industrial computing, LED Lighting and battery charger supply.



SKU: [PSU1032](#)

Specifications:

- Input Voltage Range: 100~240 VAC/1.7A/50~60Hz.
- Output Voltage Rating: 5Vdc.
- Output Current Range: 5A.
- Rated Output Power: 25W.
- Input Connector: 2-Pin.
- Output Connection Type: Ø5.5mm/ Ø 2.1mm.
- Ripple & Noise Figure: 100mV.
- Line Regulation Range: ±5%.
- Load Regulation Range: ±5%.
- Cable Length: 90cm.
- Overall Size (LxWxH): 132x58x31mm.
- Weight: 0.310Kg.

Connector Type:

Power Input Connector:

2-Pin input supply connector.



Output Cable Type:



Outer Diameter \varnothing 5.5mm



Inner Diameter \varnothing 2.1mm



Handsontec.com

We have the parts for your ideas

HandsOn Technology provides a multimedia and interactive platform for everyone interested in electronics. From beginner to diehard, from student to lecturer. Information, education, inspiration and entertainment. Analog and digital, practical and theoretical; software and hardware.



open source
hardware

HandsOn Technology support Open Source Hardware (OSHW) Development Platform.

Learn : Design : Share

www.handsontec.com



The Face behind our product quality...

In a world of constant change and continuous technological development, a new or replacement product is never far away – and they all need to be tested.

Many vendors simply import and sell without checks and this cannot be the ultimate interests of anyone, particularly the customer. Every part sell on Handsotec is fully tested. So when buying from Handsotec products range, you can be confident you're getting outstanding quality and value.

We keep adding the new parts so that you can get rolling on your next project.



www.handsontec.com

[Breakout Boards & Modules](#)



[Connectors](#)



www.handsontec.com

[Electro-Mechanical Parts](#)



[Engineering Material](#)



www.handsontec.com

[Mechanical Hardware](#)



[Electronics Components](#)

P



www.handsontec.com

[Power Supply](#)



[Arduino Board & Shield](#)

[Tools & Accessory](#)



www.handsontec.com

[Tools & Accessory](#)